



POWER PRODUCTS GENERATORS

GENERATORS

YAMAHA generators are among the most reliable products in their category, out-performing the rest.

Designed for home and backup use, YAMAHA generators are sturdy enough for all environments.

Available with petrol and diesel engines and power ranging from 1 to 26 Kva, these generators can cater to many needs.



PETROL ENGINE

MODEL	ET1	EF2600FW	EF5500EFW	EF7200E
GENERATOR	Brushless AC Generator / Single Phase	Brushless AC Generator / Single Phase	Brushless AC Generator / Single Phase	Brushless AC Generator / Single Phase
Rated Voltage (V)	220	220	220	220
Frequency (Hz)	50	50	50	50
Rated output (Kva)	0,65	2	3,8	5
Maximum Output (Kva)	0,78	2,3	4,6	6
Engine	Gasoline 2 tps.	Gasoline 4 tps.	Gasoline 4 tps.	Gasoline 4 tps.
Displacement (cm3)	63	171	358	358
Starting system	Recoil starter	Recoil starter	Electric & recoil	Electric & recoil
Fuel Tank Capacity (L)	4	12	28	28
Operating Hours (Hr)	6	10,6	12	11
Noise Level (db A)	57	65	70,7	71
Dimensions (LxWxH in mm)	367x312x375	510x415x425	670x535x565	670x535x565
Weight (kg)	19	41	90	93

DIESEL ENGINE

MODEL	EDL13000TE	EDL20000TE	EDL26000TE
GENERATOR	Brushless AC Generator Single Phase / Three Phase	Brushless AC Generator Single Phase / Three Phase	Brushless AC Generator Single Phase / Three Phase
TRated Voltage (V)	220 / 380	220 / 380	220 / 380
Frequency (Hz)	50	50	50
Rated output (Kva)	10	15,5	21
Maximum Output (Kva)	11	17	23
Engine	DIESEL	DIESEL	DIESEL
Displacement (cm3)	719	1001	1335
Starting system	Electric	Electric	Electric
Fuel Tank Capacity (L)	21	80	80
Operating Hours (Hr)	5,8	17	12,9
Noise Level (db A)	76	79	81
Dimensions (LxWxH in mm)	1020x640x770	1380x700x945	1380x700x945
Weight (kg)	260	340	380